


Leica Captivate: Updating your firmware




1	If you have a valid Customer Care Package (CCP) covering your equipment, then you can update the firmware to the latest release. Download the latest files from Leica's MyWorld portal after creating an account and registering your equipment. https://myworld.leica-geosystems.com/irj/portal	
2	When you have downloaded your update, files copy them into the "system" folder on the SD card that you use with the equipment. Then pop the card back into the device. If you have two linked devices (a controller and a Total station) both must have matching firmware versions.	
3	The first step is to back-up your settings. From the main menu select Settings followed by Tools then Transfer User Objects.	

Sunbelt Rentals Survey

3 Orpheus House, Calleva Park, Aldermaston, Reading, RG7 8TA. 0330 678 0181 Support Number: 01293 565565

sales@sunbeltsurvey.co.uk www.sunbeltsurvey.co.uk

Registered Office: Sunbelt Rentals Ltd. 100 Cheapside, London EC2V 6DT. Registered No. 444569 England & Wales




3	Select Object to transfer as All Objects, from the internal memory to the SD card and tick the box to use an AllObjects.zip file. Also tick the box Do not transfer jobs. Press OK.	
4	Once the back-up is complete, we need to format the System Ram. Head back into Settings\Tools and select Format memory.	
5	Select System and press OK. You'll get a couple of warnings at this point but OK them.	
6	This will shut down the Captivate program and take you out to the Windows desktop. Reopen Captivate by double tapping the icon on the screen.	

Sunbelt Rentals Survey

3 Orpheus House, Calleva Park, Aldermaston, Reading, RG7 8TA. 0330 678 0181 Support Number: 01293 565565

sales@sunbeltsurvey.co.uk www.sunbeltsurvey.co.uk

Registered Office: Sunbelt Rentals Ltd. 100 Cheapside, London EC2V 6DT. Registered No. 444569 England & Wales

7	Make sure your battery is >90% From there, head into Settings\Tools\Update Software	
8	And load the new version of the firmware (this will take up to 10mins)	
9	Now we can restore your original settings. From the main menu head to Settings\Tools\Transfer user objects and transfer All objects from the SD card to the Internal memory. Again, tick the box to use the zip file we created earlier.	
10	You should now be on the latest firmware and enjoying the improvements and bug fixes you've paid for.	

Sunbelt Rentals Survey

3 Orpheus House, Calleva Park, Aldermaston, Reading, RG7 8TA. 0330 678 0181 Support Number: 01293 565565

sales@sunbeltsurvey.co.uk www.sunbeltsurvey.co.uk

Registered Office: Sunbelt Rentals Ltd. 100 Cheapside, London EC2V 6DT. Registered No. 444569 England & Wales